Placing Two Handles or Knobs on a Single Drawer

Reference Number: **KB-02848** Last Modified: **July 20, 2022**

The information in this article applies to:



QUESTION

I need to have two handles or knobs on a single cabinet drawer. How can I achieve this?



ANSWER

Adding two handles or knobs to a single cabinet drawer can be accomplished using the "Two Handles In From Edge" option located within the Cabinet Specification dialog.

To place two handles or knobs on a single drawer

1. Using the **Select Objects** tool, click on the cabinet you would like to have two handles or knobs, then click the **Open Object** edit button.

In this example, a 36" wide base cabinet is used.

2. On the DOOR/DRAWER panel, under the **Drawer Handle** category:

Base Cabinet Specific	cation
General	Door
Box Construction	Main Style: Use Default ~ Library
Front/Sides/Back	
Door/Drawer	Glass Doors
Accessories	Stile Between Double Doors
Opening Indicators	
Moldings	Door Handle
Layer Fill Style	Main Style: Use Default V Library Edit
Materials	La Facera Educa 12/0"
Label	In From Edge:
Components	Down From Top: 1 3/8"
Object Information	
Schedule	Door Hinges
	Main Style: Use Default ~ Library Edit
	Up/Down From Edge: 3"
	Drawer
	Main Style: Use Default V Library
	Drawer Handle
	Main Style: CP01 Bar Pull V Library Edit
	Horizontal Position: O Use Default
	O One Handle Centered
	Two Handles In From Edge: 9"
	Vertical Position: Use Default
	○ Centered
	O Distance From Top: 0"

• Specify the **Style** of handle or knob using the drop-down menu or by clicking on the **Library** button.

In this example, the CP01 Bar Pull is specified.

• For the **Horizontal Position**, select the **Two Handles In From Edge** radio button, then enter the value the handles/knobs will be in from the outer edge of the drawer.

In this example, a value of 9" is specified.

- Specify the **Vertical Position** of the handles/knobs.
- In X14 and newer program versions, hardware properties such as the Width, Height, Depth, and Angle can be modified within the dialog by selecting the **Edit** button.

- Once the handles/knobs are specified to your liking, click **OK**.
- 3. Create a **Camera (io)** view to see the results.



Privacy Policy (/company/privacy.html)